

LM16 LED Lamp* Transformer & Dimming Compatibility

Number of allowable connected lamps and dimming range, for 50W equivalent lamps only

| DIMMER/ SERIES | MODEL NUMBER | BEI B0344F-4 REV.5 | Con-Tech LA2075N | Con-Tech LVT-300 | Fulham PET-120- 12-60 | Hatch RS12-60M | Hatch RS12-300 | Juno TL601E-75 | Lighttech LET 60 | Lighttech LET 60-LW | Lighttech LET 75 | Sea Gull 96223S- 15 |
|----------------------|-----------------|---|---|---|---|---|---------------------------------------|--------------------------------------|---|---|---|--|
| Cooper | DE06P | | 1, 2 or 3 lamps, Dimming 84% to 4% | | | | | | | 1 or 3 lamps only, Dimming 87% to 7% | | |
| Cooper | SI06P | | 3 lamps only, Dimming 95% to 0% | | | | | | | | | |
| Cooper | 9531 | | | | 3 lamps only, Dimming 75% to 1% | | | | | 3 lamps only, Dimming 63% to 0% | | |
| Leviton | IPE04-1LZ | | | | | 1, 2 or 3 lamps, Dimming 98% to 9% | | | 1, 2 or 3 lamps, Dimming 97% to 8% | | 1, 2 or 3 lamps, Dimming 98% to 8% | |
| Lutron | NLV-600 | 1, 2 or 3 lamps, Dimming 94% to 1% | | | | | | | | | | |
| Lutron | NTELV-600 | | | | | 1, 2 or 3 lamps, Dimming 89% to 3% | | | 1, 2 or 3 lamps, Dimming 92% to 2% | | 1 or 3 lamps only, Dimming 89% to 1% | |
| Lutron | RRD-6NA | | 1, 2 or 3 lamps, Dimming 88% to 0% | | 1, 2 or 3 lamps, Dimming 91% to 0% | | 1 lamp only, Dimming 100% to 0% | 1 lamp only, Dimming 90% to 0% | 1 lamp only, Dimming 90% to 0% | | | 2 lamps only, Dimming 86% to 0% |
| Lutron GRX-3104-T | ELVI-1000 | | | | | 1, 2 or 3 lamps, Dimming 87% to 0% | | | 1, 2 or 3 lamps, Dimming 85% to 0% | | 1, 2 or 3 lamps, Dimming 83% to 0% | |
| Lutron GRX-3104-T | PHPM- PA-120 | | | | | 3 lamps only, Dimming 95% to 0% | | | 2 or 3 lamps, Dimming 94% to 0% | | 2 or 3 lamps, Dimming 93% to 0% | |
| Wattstopper | SDMLV-603 | | | 1 lamp only, Dimming 93% to 1% | | | | | | | | |

* The presence of a dimmer on this chart is not a guarantee or warranty of the compatibility of the LM16 in any particular installation. The absence of a dimmer from this chart does not necessarily imply incompatibility. Please reference the dimmer manufacturer's instructions for installation and further product information.

Rev. Date: V2 03/31/2016

© 2016 Cree, Inc. and/or one of its subsidiaries. All rights reserved. Content is subject to change. For informational purposes only.
Patent www.cree.com/patents. Cree® is a registered trademark and the Cree logo is a trademark of Cree, Inc. Any other trademarks,
product and/or company names mentioned in this document are the property of their respective owners.

US: www.cree.com/lighting

T (800) 236-6800 F (262) 504-5415

Canada: www.cree.com/canada



T (800) 473-1234 F (800) 890-7507