

Field Adjustable Output

For use with Non-Cataloged OSQ™ Area and Flood Luminaires

Description:

The Field Adjustable Output option enables luminaires within the OSQ Series on this page to be tuned to the exact needs of a particular application through multiple levels of adjustment.

OSQ™ LED Area Luminaires – Input Power Designator A

Q Option Setting	System Watts 120-480V*	Lumen Multipliers	Optics Qualified on the DesignLights Consortium Qualified Products List		
	Input Power Designator A		3000K	4000K	5700K
Q9 (Factory Set)	112	1.00	N/A	40D	15D, 25D, 60D
Q8	107	0.98			
Q7	101	0.94			
Q6	96	0.91			
Q5	87	0.85			
Q4	79	0.80			
Q3	71	0.73			
Q2	64	0.68			
Q1	56	0.61			

OSQ™ LED Area Luminaires – Input Power Designator J

Q Option Setting	System Watts 120-480V*	Lumen Multipliers	Optics Qualified on the DesignLights Consortium Qualified Products List		
	Input Power Designator J		3000K	4000K	5700K
Q9 (Factory Set)	168	1.00	N/A	N/A	15D, 25D, 60D, 2ME, 3ME, 4ME
Q8	160	0.98			
Q7	152	0.94			
Q6	143	0.91			
Q5	131	0.85			
Q4	120	0.80			
Q3	108	0.73			
Q2	96	0.68			
Q1	84	0.61			

OSQ™ LED Area Luminaires – Input Power Designator S

Q Option Setting	System Watts 120-480V*	Lumen Multipliers	Optics Qualified on the DesignLights Consortium Qualified Products List		
	Input Power Designator S		3000K	4000K	5700K
Q9 (Factory Set)	223	1.00	N/A	40D	15D, 25D, 60D, 2ME, 3ME, 4ME
Q8	213	0.98			
Q7	202	0.94			
Q6	191	0.91			
Q5	175	0.85			
Q4	160	0.80			
Q3	144	0.73			
Q2	128	0.68			
Q1	112	0.61			

* Electrical and lumen data at 25°C (77°F). Actual wattage may differ by +/-10% when operating between 120-480V +/-10%



Rev. Date: V1 10/16/2018

© 2018 Cree, Inc. and/or one of its subsidiaries. All rights reserved. For informational purposes only. Content is subject to change. Patent www.cree.com/patents. Cree® and the Cree logo are registered trademarks, and OSQ™ is a trademark of Cree, Inc. The DLC QPL logo is a registered trademark of Efficiency Forward, Inc.

