



## CAUTIONS AND WARNINGS

### 150W Replacement Cree PRO Series LED PAR38

- Not intended for use with emergency exit fixtures or emergency lighting
- Risk of electric shock or burns. Turn power off and let cool before inspection or replacement
- Do not open – no user serviceable parts inside. Use only on 120 volt AC circuits
- Do not use if product is cracked, broken or missing pieces, even if lamp continues to light
- Suitable for use in operating environments ranging between -13°C and +45°C (-13°F and +113°F)
- Lifetime may be reduced is used in air tight enclosures or in insulated ceiling air tight (ICAT) recessed down light enclosures
- Suitable for wet locations where exposed directly to weather

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Visit [cree.com](http://cree.com) for more information.

#### Applicable Product Model Numbers:

- PAR38-150W-P1-30K-40FL-E26-U1